# QUICK START GUIDE

TECO StockRite Series Consistency Transmitters

## PRESENTER



**Andre Rog** 

**P&P Products Manager** 

#### QUICK START GUIDE

- A successful calibration will consist of several steps
  - Define the Sensor
  - Auto Cal the Sensor
  - Set the Strain Factor
  - Setup velocity compensation (optional)
  - Assign Consistency Values

### DEFINE THE SENSOR

 You have to tell the transmitter what sensor is being used.

Specify type, length and material


#### AUTO CAL THE SENSOR


 This procedure normalizes the response of a sensor using the force of gravity as a reference


 This is useful because you can then swap out normalized sensors and get the same reading without recalibrating

It also zeros out the effect of gravity on the sensor in its application orientation

## AUTO CAL THE SENSOR







#### SET THE STRAIN FACTOR

- The Strain Factor is a sensor gain factor
- It can be used to adjust the output of the transmitter relative to strain based on stock type
- We have pre-programmed the transmitter with strain factors for various furnish types
- These are good starting points, but may need to be adjusted later

#### SETUP VELOCITY COMPENSATION

 Velocity compensation is recommended for applications with high or variable flow rates

The C6000 accepts a 4-20ma signal for flow rate input

#### DEVIATION METER

- At this point, you have setup the system as a deviation meter
- The range of the deviation depends on the values for the consistency span and zero
- Values of 100 and 0 would output 0 to 100%


#### CONSISTENCY CALIBRATION

- If you want the transmitter to output consistencies directly, you have to adjust the values for the strain factor and the consistency span and zero
- You can let the meter calculate these for you using the built-in routine under "Compute Attributes"
- You can calculate them offline using the formula in the Appendix

#### **BUILT-IN ROUTINE**

```
SPAN LBL:
                       100.000
                                 PERCENT
       ZERO LBL:
                                 PERCENT
                         0.000
                                 %FS/F.
     STRAIN FCT:
                          1.000
           BIAS:
                        40.000
                                 PERCENT
              DESIRED LABELS.
     SPAN:
                    100.000
     ZERO:
                      0.000
              LAB RESULT
                             STRAIN SAMPLE
     TEST1:
                  EMPTY
                                 EMPTY
     TEST2:
                  EMPTY
                                 EMPTY
                          COMPUTE
                                       CNCL
     TEST #1 I
                TEST #2
     SAMPLE
                SAMPLE
                           SETTINGS
                                       QUIT
Figure 29 Typical Lab Cal Screen
```

## **CONSISTENCY CALIBRATION**



## FINISHED!

The system is now calibrated and measuring consistency